

DALI4sw – konfigurace jednoho tlačítka s vypnutím po stmívání

Krátkým stiskem se světlo střídavě zapíná a vypíná. Po připojení napájení je prvním krokem zapnutí. Dlouhým stiskem se světlo střídavě stmívá a rozsvěcí. Pokud světlo svítí (i pouze na minimální úrovni), po krátkém stisku se vypne.

Konfigurace v programu DALIconfig

Advanced settings of DALI2+ parameters

☒ Advanced settings

Commands: Commands counter 20/32

Events:

- 1 - After start
- 2 - Button pressed
- 3 - Button released
- ☒ 4 - Short press
- ☒ 5 - Long press start
- ☒ 6 - Long press repeat
- ☒ 7 - Long press stop
- 8 - Double press
- 9 - Button stuck start
- 10 - Button stuck stop
- 11 - Timer reached
- 12 - Counter comparing

N.	Command	Addr
Sequence 1:		
1	RecallMaxLevel	Bcast
2	SetNextSequence 2	
Sequence 2:		
1	Off	Bcast
2	SetNextSequence 1	
Sequence 3:		
1	Off	Bcast
2	SetNextSequence 1	

Advanced settings of DALI2+ parameters

☒ Advanced settings

Commands: Commands counter 20/32

Events:

- 1 - After start
- 2 - Button pressed
- 3 - Button released
- ☒ 4 - Short press
- ☒ 5 - Long press start
- ☒ 6 - Long press repeat
- ☒ 7 - Long press stop
- 8 - Double press
- 9 - Button stuck start
- 10 - Button stuck stop
- 11 - Timer reached
- 12 - Counter comparing

N.	Command	Addr
Sequence 1:		
1	OnAndStepUp	Bcast
2	Up, FdR7 (45/s)	Bcast
Sequence 2:		
1	Down, FdR7 (45/s)	Bcast
Sequence 3:		
1	OnAndStepUp	Bcast
2	Up, FdR7 (45/s)	Bcast

www.foxtron.cz